

For Models ▶ 3700B

Description ▶ Trimmer

CONCEPTION AND MAIN APPLICATIONS

Double insulation version of Model 3700, and it provides the operators safety work protecting from electric shock.

► Specifications

Voltage	100 V
Current	3 A
Cycle (Hz)	50 - 60 Hz
Continuous Rating Input	440 W
No load speed	28000 rpm.
Collet capacity	6 mm or 1/4"

► Standard equipment

Trimmer Guide Assembly	1 pc.
Straight Guide Assembly	1 pc.
Templet Guide	1 pc.
Carbide-Tipped Straight Bit	1 pc.
Wrenches	2 pc.
Collet Cone 6mm or 1/4"	1 pc.

► Optional accessories

- Sash Router Base Assembly
- Trimmer Shoe
- Trimmer Bits mentioned in our general catalogue

► Repair

1. Mounting of Switch
Switch has to be mounted with making sure that "ON" - "OFF" positions of switch lever conform to the "ON"- "OFF" indication on the motor rear housing.
2. Dismounting of armature from the motor housing
After dismounting of collet nut, collet cone and carbon brushes from the armature shaft, take off the armature section (including motor rear housing). and then armature can be taken off from the motor rear housing.
However, do not hit the motor rear housing.
3. Pay attention that the set screw fastening the guide roller is left-handed one.

