




CONCEPTION AND MAIN APPLICATIONS

This new Belt sander has been developed from 9401 into Electric two-speed function.



Specifications

| Voltage(V) | Current(A) | Frequency(Hz) | Consumed power(W) |
|------------|------------|---------------|-------------------|
| 100 V | 12 A | 50-60 Hz | 1140 W |

| Belt speed | (H) 350 m/min. | (L) 300m/min. |
|-------------|----------------|---------------|
| Belt size | 100 x 610 mm | |
| Weight | 7.3 kg | |
| Cord Length | 5 m | |

► Standard equipment

Step

Carbon plate

Each type of sanding belt

Optional accessories

Steel plate:

Each type of sanding belt(5 pieces in one set)

► Repair

Although same as #9401, the lead wire inside the handle has been increased due to the installation of two speed switch. Accordingly use care that the lead wires are not locked together in assembling the handle cover.